



Notes:

1. Coax cables shown connecting from face 1 to face 2 to face 3 to face 4 supplied by Nevco.
2. Power cables for each face supplied by Nevco
3. This sign is intended to be installed in accordance with the requirements of Article 600 of the National Electric Code and/or other applicable local codes. This includes proper grounding and bonding of the sign.

Total 4-Face Board Power								
Model	Amps (120VAC)				Amps (240VAC)			
	-NL	-RL	-ETN-NL	-ETN-RL	-NL	-RL	-ETN-NL	-ETN-RL
2700/2702	3.3	3.6	4.2	N/A	1.7	1.8	2.1	N/A
2710/2712	4.0	4.5	4.8	5.1	2.0	2.2	2.4	2.5
2750	4.0	4.7	4.7	5.3	2.0	2.3	2.4	2.6
2770/2772	4.1	5.0	4.9	5.6	2.0	2.5	2.5	2.8
4710	4.64	5.16	5.5	5.8	2.3	2.6	2.75	2.9
4711	5.48	6.12	6.3	6.7	2.75	3.05	3.15	3.35
4750	5.08	5.76	5.9	6.4	2.55	2.9	2.95	3.2
4770	3.36	4.04	4.6	4.24	1.68	2.02	2.3	2.12

4-Face Wired Installation	<p>Nevco, Inc. Greenville, Illinois 62246</p>	
Last ECO	Sheet 1 of 1	
Drawn DLP	Date 9/12/2014	